

# Recessed Mini Door / Window Sensor

## Wireless, Supervised Sensor

- Easy to install.
- Easy to “Learn” into 319 MHz wireless control panels.
- Compact size: 2 .25” L x .75” Dia.
- Signals: supervisory, tamper, and low battery.
- Dual tamper; sensor and case for added security.
- Effective with vertical or horizontal mount.
- Replaceable extra long-life battery: 1-VDC lithium.
- Smaller and narrow switch package.
- Superior RF range and performance, even on steel surfaces.
- Wireless sensors and detectors built with MaxOut™ Technology for maximum Radio Frequency (RF) security sensor reliability. MaxOut high performance sensors deliver the maximum FCC allowable output for maximum signal strength and range.

The Recessed Mini Door/Window Sensor is a supervised, wireless sensor that detects the opening and closing of doors or windows. New, high-powered Microchip delivers exceptional range; 360° with no dead spots or signal drop-offs.

Patented design with an isolated antenna above board and separated from batteries for superior RF performance and transmission efficiency. Reduced interference from metal door and window frames. Reduced battery energy draw lengthens the battery life.



## Specifications

Model Number:	RF-RDWS-319-NN
RF Frequency:	319.5 MHz
Compatibility:	319.5 MHz control panels. Interlogix® GE®, ITI® and Qolsys®
Battery Type: (Requires 1)	3-VDC Lithium Battery, Varta or Panasonic CR2
Operating Temperature Range:	32 to 120°F (0 to 49°C)
Storage Temperature Range:	-30 to 140°F (-34 to 60°C)
Relative Humidity:	95% Non-Condensing
Dimensions (L x Diameter):	Sensor: 2.25 in. x .75 in. Magnet: 1 in. x .7/8 in.